

# CNR-DS1100 Pro Series

Linux-embedded Standalone NVR



<b>5 CH CNR-DS1105 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 5ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 5+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 5ch	Local Display Monitoring		Modes	1, 4, 5+1, full screen, sequential	<b>9 CH CNR-DS1109 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 9ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8,9, 5+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 9ch	Local Display Monitoring		Modes	1, 4, 8,9, 5+1, full screen, sequential	<b>12 CH CNR-DS1112 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 12ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8, 9,10,12, 5+1/12+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 12ch	Local Display Monitoring		Modes	1, 4, 8, 9,10,12, 5+1/12+1, full screen, sequential	<b>16 CH CNR-DS1116 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 16ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8, 9,10,12,16, 5+1/12+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 16ch	Local Display Monitoring		Modes	1, 4, 8, 9,10,12,16, 5+1/12+1, full screen, sequential
Video Recording																																			
CH No.	Up to 5ch																																		
Local Display Monitoring																																			
Modes	1, 4, 5+1, full screen, sequential																																		
Video Recording																																			
CH No.	Up to 9ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8,9, 5+1, full screen, sequential																																		
Video Recording																																			
CH No.	Up to 12ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8, 9,10,12, 5+1/12+1, full screen, sequential																																		
Video Recording																																			
CH No.	Up to 16ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8, 9,10,12,16, 5+1/12+1, full screen, sequential																																		
<b>20 CH CNR-DS1120 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 20ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8, 9,10,12,16, 20, 5+1/12+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 20ch	Local Display Monitoring		Modes	1, 4, 8, 9,10,12,16, 20, 5+1/12+1, full screen, sequential	<b>25 CH CNR-DS1125 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 25ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 25ch	Local Display Monitoring		Modes	1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential	<b>32 CH CNR-DS1132 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 32ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 32ch	Local Display Monitoring		Modes	1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential	<b>36 CH CNR-DS1136 Pro</b> <table border="1"> <tr><th colspan="2">Video Recording</th></tr> <tr><td>CH No.</td><td>Up to 36ch</td></tr> <tr><th colspan="2">Local Display Monitoring</th></tr> <tr><td>Modes</td><td>1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential</td></tr> </table>	Video Recording		CH No.	Up to 36ch	Local Display Monitoring		Modes	1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential
Video Recording																																			
CH No.	Up to 20ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8, 9,10,12,16, 20, 5+1/12+1, full screen, sequential																																		
Video Recording																																			
CH No.	Up to 25ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential																																		
Video Recording																																			
CH No.	Up to 32ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential																																		
Video Recording																																			
CH No.	Up to 36ch																																		
Local Display Monitoring																																			
Modes	1, 4, 8, 9, 10, 12,16, 20, 25, 5+1/12+1, full screen, sequential																																		

## Main Features

- Real-time Liveview Local Display
  - Dual Display via HDMI/VGA
- Real-time Remote Browser Monitoring
  - Up to 36CH of single server
  - Liveview Display Modes: 1,4,8,9,10,12,16,20,25,30,36, 46, 49, 5+1/12+1, full screen and sequential mode
  - Built-in Mini-CMS server (up to 144CH)
  - Various Web Browsers in Windows OS
  - Quick Navigation with Dynamic E-Map
  - Multi-window Operation
- Excellent Megapixel Real-time Video Recording
  - 2 Megapixel Recording Resolution
  - Support 60FPS Camera Recording and Monitoring on Local Display and Remote Browser
- Multi-channel Playback on Remote Browser
  - Maximum 16-channel playback simultaneously
  - Event Instant Playback on Liveview and E-Map
  - Smart Search
- Monitoring everywhere via iOS and Android mobile device
- Multi-volume Storage Management with DIGIARRAY
  - Up to 30TB Storage Capacity (Up to 6TB per HDD) (NVR: 6TB + DIGIARRAY Storage Expansion Units: 24TB)
- Diverse Backup Methods
  - Export Files from Remote and Local Playback
  - Instant Export while Playback on Remote
  - One Touch USB Backup
  - Remote Backup to NAS
  - Cloud Backup to Dropbox
  - Export File with Free-Installation Video Player
- Powerful Event and Action Management
  - Detection of Device Connection Lost, External Events and Camera Motion/ IVA
  - Notification via Liveview Pop-out Window, Email, SMS, Buzzer and External Devices
- Advanced and Reliable Security System
  - Reliable Linux Security System
  - NVR Failover and System Monitoring
  - Detailed Complete log Information
  - Flexible User Privilege Management



Compatible Network Camera Brands and Partners



Technical Alliance asustor, AXIS ADP Program, intel inside, ONVIF, Seagate, WD

# Technical Specifications

System	
Operating System	Linux-embedded
CPU	Intel Dual Core CPU
HDD Tray	1 (Internal)
Maximum Capacity	Up to 6TB (2.5"/3.5" SATA HDD x 1)
LAN Port <sup>2</sup>	Gigabit x 1
USB Connector	USB3.0 x 2 (Rear), USB2.0 x 4 (Front x 2, Rear x 2)
Video Output Connector	HDMI x1, DVI-I x1 (For Dual Display)
Disk Management	Single
Operating Temperature	0~40°C
Operating Humidity	0~95% R.H.
Power Supply	External power adaptor, 90W Input :19VDC, 4.74A
Power consumption	38.5W~45W (with 1 x 1TB HDD installed and in Single building process)
H/W Dimensions	59(H) x 237(W) x 192(D) mm 2.3(H) x 9.33(W) x 7.56(D) inch
User Interfaces	(1) Remote Web Browsers: Microsoft® Internet Explorer/ Chrome /Firefox /Opera / Safari in Windows (32-bit) (2) Local display monitoring (3) Mobile App: Android and iOS
Supported Languages	Croatian, Czech, Dansk, Deutsch, Dutch, English, Finnish, French, Indonesia, Italian, Japanese, Korean, Hungarian, Norwegian, Polish, Portuguese, Russian, Spanish, Swedish, Thai, Turkish, Tradition Chinese, Simplified Chinese, Vietnamese

Playback	
Multi-channel Playback <sup>6</sup>	Maximum 16-channel simultaneously
Recording Types	Normal, Event, Video clip, Recovery and Time overlap
Search Modes	Date, time, channel and recording type
Smart Search	Motion detection, Foreign object detection, Missing object detection, Camera tampering detection, Lose focus
Playback Control	Rewind, Slow motion, Fast forward, Frame by Frame Playback, Panomorph <sup>7</sup> , Snapshot
Backup Methods	Export Files from remote and local playback, One touch USB backup, Remote backup to NAS, Cloud backup, Instant export while playback videos on remote
Video Player	Installation-free NVRPlayer with multi-channel playback


Event & Action Management	
Event Types	Camera connection lost, NVR connection lost, Motion detection, Camera digital input and External event (HTTP in), Recording error
Action Types	Alert sound, Event log notification, Video pop-out window, Highlight video window, Event recording, E-mail notification, Video clip/ snapshot via E-mail, User defined action, Buzzer alarm, SMS, Go to PTZ preset point, External I/O box, Camera digital output

Liveview	
Liveview Control	PTZ panel, PTZ Patrol, Auto Focus, Digital zoom in/out, Audio, Snapshot, Auto/Manual stream change, Event instant playback, Two way audio <sup>6</sup> , Panomorph <sup>7</sup>
E-Map <sup>3</sup>	Multi-layer maps, Pop-out event window, Event instant playback
Mini-CMS Server Monitoring <sup>3</sup>	Up to 144 channels from multiple NVR sites
Liveview Optimization	Smart dual stream auto switch
H/W Decode Local Display Max. FPS in Single Page <sup>4</sup>	Full HD 200FPS/ HD 300FPS/ D1 750FPS (H.264)

Security Management	
User Privilege	Administrator, Power user and User
System Log Information	Hardware log, System log, Event log, File access log, Current user log and Historical user log
NVR Failover	Monitor up to 4 NVRs in default (Option up to 16 NVRs)
IP Range Access Control	White/Black List to permit or prohibit specific IP address
Timeout Setting	Set up auto timeout period
Advanced Security	Video Watermark and Password on exported video file

Recording	
Recording Modes	No recording, Event recording, Schedule recording, Always recording, Audio recording by event, Pre-event and Post-event recording
HDD Capacity Automatic Recycle	(1) Max. days (2) Total capacity percentage
File format	AVI
Video Format	H.264 · MPEG4 · MJPEG
Max. Network Throughput <sup>5</sup>	360Mbps

Network Service	
Protocol	HTTP · HTTPS · TCP/IP · DHCP · DNS · DDNS · UPnP · FTP · NTP · SMTP
File Sharing	Windows networking · FTP service
Built-in Servers	Built-in DHCP/NTP Server

Appearance	
	<ol style="list-style-type: none"> <li>1. Power button</li> <li>2. LED indicators: HDD</li> <li>3. USB 2.0 x 1 (Support auto video backup)</li> <li>4. USB 2.0 x 1</li> <li>5. Power connector</li> <li>6. USB 3.0 x 2</li> <li>7. DVI-I</li> <li>8. eSATA x 1 (reserved)</li> <li>9. HDMI x 1</li> <li>10. Gigabit LAN x 1</li> <li>11. USB 2.0 x 2</li> <li>12. Audio mic input (reserved)</li> <li>13. Audio output (reserved)</li> </ol>

Remote Web Browser PC Requirements	
OS (32 and 64-bit)	Windows Vista / 7 / 8
CPU	< 16CH: Intel Dual Core CPU 3.0GHz or above ≥ 16CH: Intel i5/i7 CPU 3.3GHz or above
Memory	< 16CH: DDR3 4G or above ≥ 16CH: DDR3 8G or above

\* All designs and specifications are subject to change without prior notice.

Note1. The standard system is shipped without HDD.

Note2. User is advised to connect cameras and NVR with gigabit switch

Note3. E-Map and Built-in Mini-CMS Server Monitoring is not supported on local display.

Note4. The max. resolution on liveview and playback of local display supports up to Full HD. Remote web browser's max. resolution is the same as recording.

Note5. Maximum network throughput is varied in different environment.

Note6. Multi-channel playback on remote web browsers is supported up to 16 channels and multi-channel playback on local display is supported up to 4 channels.

Note7. NVR supports dewarping display image of ACTI, AXIS, VIVOTEK,

Immersion Panombrp and fisheye camera



3706 Alliance Drive, Greensboro, NC 27407  
1-888-50-CREST  
CrestElectronics.com