

# CDA-5 Video Distribution Amplifier



- 👉 This amplifier receives a single input signal, isolates and then provides four independent video outputs
- 👉 Dual voltage – 24vAC / 12vDC
- 👉 12vDC transformer included

 **CREST**  
ELECTRONICS INC  
Video Security Since 1974

# Product Data: CDA-5 Video Distribution Amplifier

<b>Model Number</b>	<b>CDA-5</b>
<b>Video Input</b>	1-2v p-p, 75 ohm, 1 input
<b>Video Outputs</b>	1-2v p-p, 75 ohm, 4 outputs
<b>Video Gain</b>	Unity
<b>Frequency Response</b>	2.5Hz to 15MHz to +/-0.3dB
<b>Bandwidth (-3dB)</b>	1Hz to 15MHz
<b>Input Voltage</b>	12vDC/24vAC
<b>Power Consumption</b>	5w
<b>Video Connectors</b>	BNC
<b>Construction</b>	ABS black plastic
<b>Dimensions</b>	5 3/8" w x 1 1/16" h x 3 3/8" d
<b>Weight</b>	4 oz

*Specifications subject to change*

