


## 1 . OPERATION

Power on the DVR system , the real-time video can be seen by 4 quad screen or full screen display .  
User can press "MODE" button to switch the display mode .

**Playback mode :** Press "PLAY" button , user can search date-time to playback .

**Record mode :** Press "REC" button start to record . User can press "SHIFT" + "MODE" button to change the record quality .Record quality level have 5 types : HST / HIG / NOR / LOW / LST .


Press "SHIFT" button , it will show an icon  at top line on screen then press "MODE" button to change record frame rate and quality level then it will show a message **HST** on top-right screen .  
User change the different record level , it means that user change the record quality , below table show the mapping .

Level	HST	HIG	NOR	LOW	LST
FPS	60 (15/each)	60 (15/each)	16 (4/each)	8 (2/each)	8 (2/each)
Quality	High	Normal	Normal	Normal	Low

### Backup mode :

Before backup, USB device is required. User need insert USB device into USB slot before backup.  
Backup file size can not exceed 3GB

1. On playback mode, press "SHIFT" button to start backup.
2. When user press "SHIFT" button , it means the start time of backup .
3. When user press "SHIFT" button second time , it means the end time of backup .
4. The system will auto reading USB device then start to backup data .



## Search

User can search record data by time search , press "PLAY" button and input time to search video .

1. Press "ENTER" into time select .
2. Use direction left or right button to move the cursor position .
3. Press "ENTER" to change date and time .



4. Press "MENU" return to the previous screen and move cursor to Search.
5. Press "ENTER" to start the searching.
6. Wait until the unit starts to playback.



## Playback mode

Forward speed: x 2 / x 3 / x 4

(Direction right button)

Reverse speed: x 8 / x 16 / x 32

(Direction left button)

Press "STOP" button return to live mode.

## Notice :

In real-time mode , user can press direction key "Up ▲" 5 times to enable key lock .

And press direction key "Up ▲" 5 times again to disable key lock